USER'S GUIDE

YP12598N(MULTI FUNCTION SPORT LCD WATCH) CITIZEN WATCH CO.,LTD. Q&Q SALES DEPARTMENT



Quartz Movement



Stopwatch



Calendar




Chime



Battery(CR2016 +SR626SW)

BUTTONS

. The operation of buttons are indicated using the letters shown in the illustration.



- C -- EL backlight
- D -- Start / Stop

ATTENTION

- 1. Never try to open the case or remove its back cover.
- 2. Do not operate buttons underwater.
- 3. Should moisture appear inside the watch, have it checked immediately by your dealer. Otherwise it can cause erosion of the metal parts of the watch.
- 4. Though the watch is designed to withstand normal use, you should avoid rough use or dropping the watch.
- 5. Avoid exposing the watch to temperature extremes.
- 6. Wipe the watch with dry, soft cloth only. Avoid allowing it to come into direct contact with chemical materials, which can cause deterioration of the plastic parts of the watch.
- 7. Avoid to wear the watch in electromagnetic, static conditions.

MODE SELECTION

• Press "B" to change mode to mode in the following Sequence: Timekeeping Mode + Stopwatch Mode + Alarm Mode + Time Setting Mode.



- · Hour, Minutes, Seconds, Day of week:
- · Builld in Date.

(b) STOPWATCH

- 1/100 second unit:
- · Measuring range: 0'00"00 ~ 23:59'59".



- · The alarm sounds at the preset time each day;
- · Hourly time signal;
- · Snooze for 5 minutes.


(d) TIME SETTING

· Hour, Minutes, Seconds, Month, Date, Day of week can be set.



DISPLAY

· The screen shown in below:



ADJUST HANDS

- Pull out the crown, turn to adjust the hour and minutes hands:
- Push the crown go back the normal position after the time set



TIMEKEEPING

Display The Date

· In the timekeeping mode, press and hold "D" to display the date.

On/Off The Alarm

- 1. In the timekeeping mode, press and hold "A" display the alarm time:
- 2. Press "D" at the same time to on/off the alarm.

2. Press "B" at the







On/Off The Chime

- 1. In the timekeeping mode, press and hold "A" display the alarm time:
- same time to on/off the chime.









C) ALARM

Alarm Time Setting

- 1. In the alarm mode. the hour to flash;
- 2. Press "D" to increase the hour, press and hold to increase at high speed;

3. Press "A" to select

the minutes:



4. Press "D" to increase the minutes, press and hold to increase at high speed;



5. Press "B" to return the timekeeping mode, after you set.

Snooze

- . The alarm sounds at preset time each day for about 60 seconds;
- · Press "D" to break it, the alarm continue after 5 minutes:
- · Press "A" to stop it.

STOPWATCH

A Lap Time

- 1. In the stopwatch mode, press "D" to start the stopwatch;
- 2. To stop the stopwatch by pressing "D" again;
- 3. Press "A" to reset the stopwatch

Split Time

- 1. In the stopwatch mode. press "D" to start the stopwatch:
- 2. Press "A" to display the split time, stopwatch timing continues internally;
- 3. Press "A" to clear the split time and to continue time measurement;
- 4. Repeat step 2 and 3, you can measure the multi split time:
- 5. Press "D" to stop the stopwatch.

d TIME SETTING

Time Setting

- 1. In the time setting mode, the seconds to flash:
- 2 Press "D" to reset the seconds:
- 3. Press "A" change to the next selection;
- 4. Press "D" to increase the number, press and hold to increase at high speed;



- 5. Repeat step 3 and 4, the selection in the following sequence: Seconds - Minutes - Hour - Date - Month - Day of week:
- 6. Press "B" to return the timekeeping mode, after you set. • 12 / 24H formats can be selected, when hour setting.

BACKLIGHT

• The backlight that uses an EL (electroluminescent) cause the display to glow for easy reading in the dark.

Use EL Backlight

· In any mode, press "C" to illuminate the display about 3 seconds.





